

CONTROLADOR DMX



Model No.: DMX-192C

Power Input	9 ~ 12V DC 500mA In
DMX In/Out	3 Pin Female/Male XLR
Midi In	5 Pin Multiple Socket
Dimension	L482 x W135 x H90 mm
Weight	2.7kgs



FEATURE:

- > 192DMX channels
- > 12 Scanners of 16 channels each
- > 30 Banks of 8 programmable scenes
- > 6 Programmable chases of 240 scenes
- > 8 Sliders for manual control of channels
- > Assignable joystick for ease of channels
- > File Dump allows data to be sent or receive between two units
- > Auto mode program controlled by speed and fade time sliders
- > Fade time/Assign fade time
- > Reversible DMX channels allows fixture to react in opposition to others in a chase
- > 8 CHANNEL or 16 CHANNEL mode
- > Fine adjustment for joystick pan and tilt
- > Blackout master button
- > Manual Override button allows you to grab any fixture on the fly
- > Built in microphone for music triggering
- > MIDI control over banks, chases and blackout
- > DMX Polarity selector
- > Power failure memory

Fonos /fax (56-2) 699.07.05 - 699.07.89 email lantec@lantec.cl
Dirección : Maturana N°704 (Barrio Brasil) Santiago – Chile
www.lantec.cl