

LED CONTROLLER DIGITAL TYPE



Fonos /fax (56-2) 699.07.05 -
699.07.89 email
lantec@lantec.cl
Dirección : Maturana N°704
(Barrio Brasil) Santiago –
Chile
www.lantec.cl

Model No.: CTR-DIGITAL-12V

Dimension	L182 x W147 x H56 mm
Weight	0.92kgs
Working Volt.	12V DC
Protection	IP20
Power Consumption	2.8Watts
Signal Output	5 Pins Connector

With DMX 512 input & output port

Function Display	Description
1 BLACK	BLACK OUT
2 STATIC RED	STATIC RED
3 STATIC GREEN	STATIC GREEN
4 STATIC BLUE	STATIC BLUE
5 STATIC YELLOW	STATIC YELLOW
6 STATIC PURPLE	STATIC PURPLE
7 STATIC CYAN	STATIC CYAN
8 STATIC WHITE	STATIC WHITE
9 COLOR CHANGE	7 COLOR CHANGE
10 FLOW CHASE1	CHASE FR THE FIRST IN SECTION
11 FLOW CHASE2	CHASE FR THE END IN SECTION
12 COLOR CHASE	COLOR CHASE
13 CORUSCATE RUN	CHASE FR THE FIRST IN TUBE
14 FAST FLOW1	CORUSCATE RUN
15 FAST FLOW2	CHASE FR THE END IN TUBE
16 ROLL CHASE	ROLL CHASE
17 ROLL COLOR	ROLL COLOR
18 MULTICOLOR1	MULTICOLOR CHANGE1
19 MULTICOLOR2	MULTICOLOR CHANGE2
20 MULTICOLOR3	MULTICOLOR CHANGE3
21 STROBE FLOW	STROBE FLOW
22 FROM MIDDLE	CHASE FROM MIDDLE TO SIDE
23 FROM SIDE	CHASE FROM SIDE TO MIDDLE
24 R&G FLOW	RED & GREEN FLOW
25 G&B FLOW	GREEN & BLUE FLOW
26 R&B FLOW	RED & BLUE FLOW
27 R&G CHASE	RED & GREEN CHASE
28 R&B CHASE	RED & BLUE CHASE
29 Y&P CHASE	YELLOW & PURPLE CHASE
30 FADING1	SMOOTH FADING1
31 FADING2	SMOOTH FADING2
32 RAINBW	RAINBOW CHASE
33 AUTO PROGRAM	AUTO RUNNING
34 DMX512	DMX512 MODE
35 TUBE CODING	TUBE ADDRESSING